R.K. Instruments & Controls

TECHNICAL DATASHEET

FLOW & FLAME CONTROL | Office No. 12, 1st Floor, Dhamanwala Service Complex, G.I.D.C., Pandesara, Surat - 394221, Gujarat, India
Phone: +91 9824136145 Email: rkic1976@gmail.com Web: www.rkic.in

Honeywell Ignition Transformer ET 401A (230V AC)

Brand: Honeywell Technologies | Code/Part No.: ET 401A | Category: IGNITION TRANSFORMERS

Specifications

Type	**ET 401A**
Primary	**230V, 0.25A, 50/60 Hz**
Secondary	**14kV Ampl., 35mA rms**
Duty Cycle	**AB 33%, ED in 3 Min.**
Protection	**IP40**
Wiring	**Blue-N, Brown-L, Green&Yellow-E (flying leads)**
Origin	**Made in China**
Manufacturer	**Honeywell**



Description

The Honeywell ET 401A is an ignition transformer that steps up a 230V mains supply to a 14kV high-voltage secondary output rated at 35mA rms, for firing the spark electrode on gas and oil burners. Rated for an intermittent duty cycle of 33% ED (energised duration) within a 3-minute cycle, with IP40 protection, it delivers reliable high-voltage ignition for burner and boiler applications. It terminates in flying leads (Blue-N, Brown-L, Green&Yellow-E) for direct wiring into the burner control circuit. Manufactured by Honeywell.

Typical media compatibility: CNG, PNG, LPG, Air, Nitrogen — confirm against application before installation.