R.K. Instruments & Controls

TECHNICAL DATASHEET

FLOW & FLAME CONTROL | Office No. 12, 1st Floor, Dhamanwala Service Complex, G.I.D.C., Pandesara, Surat - 394221, Gujarat, India
Phone: +91 9824136145 Email: rkic1976@gmail.com Web: www.rkic.in

Brahma Flame Relay Sensor RE3 (240V) — Code 10801075

Brand: Brahma | Code/Part No.: 10801075 | Category: FLAME RELAY

Specifications

Type	**RE3**
Code	**10801075**
Voltage	**240 V**
Frequency	**50–60 Hz**
Power	**3 VA**
Safety Time (TS)	**max. 1 s**
Indicators	**Power (green LED), Flame (red LED)**



Description

The Brahma RE3 is a flame relay module that takes the signal from a flame sensor (UV cell or photocell) and converts it into a switched relay output confirming flame presence, with a fast maximum safety time of 1 second. Front-panel Power and Flame LED indicators give an instant visual check of supply status and flame signal. This 240V variant (code 10801075) runs on a 240V, 50–60Hz, 3VA supply, manufactured by Brahma, Italy for burner and boiler flame monitoring and safety circuits.

Typical media compatibility: CNG, PNG, LPG, Air, Nitrogen — confirm against application before installation.